

Locking Spacers

For further product information, please consult the applicable Technical Drawing online.

LOW PROFILE SELF-LOCK SPACERS

- Material: Nylon 6/6 UL94V-2.
- Spacer design uses minimum board area.
- Recommended PC board thickness 1.60mm.
- Recommended hole size Ø4.00mm.







ORDER CODE	LENGTH	
R6003-00	3.2	
R6006-00	6.3	
R6008-00	8.0	
R6009-00	9.5	
R6010-00	10.5	
R6013-00	12.7	

RIGID SELF-LOCK SPACERS

- ► Material: Nylon 6/6 UL94V-2.
- Spacers have wide ribs with locking fingers to provide a secure, rigid fit with extra stability.
- Recommended PC board thickness 1.60mm.






ORDER CODE	LENGTH
R6405-00	4.8
R6406-00	6.4
R6410-00	9.6
R6413-00	12.7
R6416-00	15.9
R6419-00	19.1
R6422-00	22.2
R6425-00	25.4
R6428-00	28.5
R6435-00	35.0

SCREW FIXING SELF-LOCK SPACERS


- Material: Nylon 6/6 UL94V-2.
- ► Fit spacer to underside of upper board, then attach lower board to bottom of spacer with No. 6 (1/8") screw.
- Recommended hole sizes: Ø4.00mm (upper board), Ø3.60mm (lower board).
- Recommended PC board thickness 2.00mm (upper board).




ORDER CODE	LENGTH
R6505-00	4.9
R6510-00	9.6
R6513-00	12.7
R6519-00	19.1
R6528-00	28.5
R6535-00	35.0

REVERSE LOCK SPACERS

- Material: Nylon 6/6 UL94V-2.
- Fit spacers from underside of board.
- Recommended PC board thickness 0.50 1.80mm.
- Recommended hole sizes: Ø4.00mm (upper board), Ø5.50mm (lower board).





ORDER CODE	LENGTH
R6706-00	6.1
R6708-00	8.0
R6710-00	9.8
R6712-00	12.0
R6714-00	14.0
R6718-00	18.0

All dimensions in mm.

